


Printing of "raised adhesive dots"

Using Standard Laser Cut Stencils

Typically 200µ ~ 500µ thick

Varidot
Thin Plastic Stencils
1mm thick



Pump Print

Thick Plastic Stencils
3 ~ 10mm thick

Printing with plastic stencils [a Novatec patented technology] generates a better dot height



Guidance Notes:


Laser cut metal stencils can be cleaned of adhesive in a similar manner to solder paste ~ However the glue will penetrate and stain the foam pad.

The following 9 STEPS cover cleaning plastic stencils but equally apply to cleaning laser cut metal stencils. Use open shallow tray or SCC with foam pad removed

- Selection of cleaning fluid is very important and must be matched to the adhesive.
- Stencil Cleaning Centre have a adhesive cleaning option.



STEP 1 ~ Remove ALL surface excess material with spatula & impregnated wipe cloth







STEP 2 ~ Using Compressed Air - blow through apertures

Support stencil 30mm
Away from USC paper








Use Compressed air gun

or the specially developed Novatec aperture cleaner tool





STEP 3 ~ Adhesive held in apertures is trapped on paper



Dispose of dirty paper



STEP 4 ~ Place 3mm thick stand off strips in cleaning tray



To support outside of image area

STEP 5 ~ Place Stencil on Strips





STEP 6 ~ Fill cleaning tray so fluid JUST covers stencil



Move transducer gently & slowly over image area 60 ~ 90 second only


STEP 7 ~ Apply transducer





STEP 8 ~ Leave Stencil Standing in cleaning fluid for 4 minutes

STEP 9 ~ Apply Transducer to apertures until they are clear







Why 9 STEPS?

- Airline opens up the cleaning area allowing fluid a greater surface area to contact
- Stand off allows fluid to flow through apertures (mini ultrasonic tank)
- First Ultrasonic cycle ensures fluid penetrates the layer of adhesive
- Soak for 4 minutes helps break down of the adhesive
- Second Ultrasonic cycle removes all trapped material.


Notes:

- Ensure the fluid is matched to the properties of the adhesive
- Only JUST cover surface of stencil

Do Not Immerse Transducer



Stencil Cleaning Centre ~ Adhesive Cleaning Options



- 30mm deep tray ~ cross corner creases
- Centre drain point 12mm drain hole
- Drain off pipe work with tap
- 3mm stand off strips (2)

